

RUGGED. RELIABLE. RESPONSIVE.

ZEBRA L10 WINDOWS TABLET DOCKING STATION

Rugged products designed for your work environment.

Designed for the Zebra L10 Windows rugged tablet, Gamber-Johnson's L10 Windows docking station is compatible with the Zebra L10 xPad hard-handle tablet and xSlate tablet. The L10 Windows tablet docking station provides port replication that includes a powered RS232 port to attach scanners for a warehouse or forklift solution, and USB 2.0 ports for a multitude of mobile applications to connect with peripherals. The L10 Windows docking station features convenient LED indicator lights that help you know when the tablet is connected to the docking station and when the dock is powered. The keyed-lock provides added security and theft deterrence.

WEIGHT	HEIGHT	WIDTH	DEPTH			
3.75 lbs / 1.70 kg	10.63 in / 27.0 cm	11.81 in / 29.9 cm	3.94 in / 10.0 cm			

CERTIFICATES & TESTING

- · Zebra Certified
- · Vibration Tested: MIL-STD 810G Operational/Non-Operational
- Shock Crash Hazard: SAE J1455; Mechanical Shock: 40G
- Cycle Test: Latch, Lock, and Docking Connector 30,000 Cycles
- Environmental: Thermal Shock; High/Low Temperature Operational & Storage
- FCC, CE, RoHS, WEEE Certified





FEATURES

- Compatible with the Zebra Windows L10 xPad hardhandle and xSlate tablet computer
- Design accommodates the L10 extended battery, smart card/CAC reader module, True Serial (RS232) module, hard handle, soft handle, and shoulder strap
- Sealed docking connector to protect against moisture
- RS232 power pin 9 (825mA)
- LED indicator lights show that "tablet is docked" and "dock is powered"
- Access door to internal USB 2.0 port provides additional security
- Floating docking connector for reliable docking activation
- Bottom-facing I/O ports; integrated cable restraint/cable management system
- Forward facing docking latch/release for easy onehanded operation:
- Insert bottom of computer into docking station, push top of computer in and pull latch forward until latch engages
- To remove, lift latch to disengage and pull computer out of docking station
- Keyed lock for security and theft deterrence
- VESA 75 and 50mm x 100mm mounting patterns
- Rounded edges to enhance personal safety
- Composite/aluminum design for reduced weight and durability
- 3-Year Limited Warranty
- NOTE: Serial communication through the docking station with the L10A is not supported.



ZEBRA L10 WINDOWS TABLET DOCKING STATION



MICROPHONE

PORT REPLICATION

- Zebra Certified Electronics
- USB 2.0 (2) 9 Pin (900mA)
- USB 2.0 (2) 4 Pin (500mA)
- USB 2.0 (1) 4 Pin (500mA) behind access door
- RS232 Serial (1) Power on Pin 9
- Microphone (1), Headphones/Speakers (1)
- Power Input: 19 VDC

ACCESSORIES

- Item No. 7300-0484 LIND Automotive Power Adapter 12-16V
 Bare Wire
- Item No. 7300-0344 LIND Automotive Power Adapter 12-32V
- Item No. 7300-0345 LIND Automotive Power Adapter 12-32V
- Cigarette Lighter Connector • Item No. 7300-0027 - LIND Material Handling Isolated Power Adapter 12-32V Bare Wire
- Item No. 7300-0458 LIND Material Handling Isolated Power Adapter 20-60V Bare Wire
- Item No. 7300-0346 LIND Material Handling Isolated Power Adapter 72-110V Bare Wire

PRODUCT SELECTION

ITEM NUMBER	ZEBRA L10 DESCRIPTION	USB 2.0	USB 2.0 FAST Charging	RS232 SERIAL	MIC/ HEADPHONES	POWER ADAPTER INCLUDED	ANTENNA RF
7110-1292	Cradle NO RF (no electronics)						No
7160-1321-00	Windows Docking Station No RF	3	2	1	1 each	No	No
7160-1321-01	Windows Tablet Docking Station Module	3	2	1	1 each	No	No
7160-1321-05	Windows Docking Station 5X	3	2	1	1 each	No	5X
7170-0799	Windows Docking Station No RF with 12-16V Auto Power Adapter	3	2	1	1 each	Yes	No
7170-0800	Windows Docking Station No RF with 20-60V Isolated Power Adapter	3	2	1	1 each	Yes	No
7170-0801	Windows Docking Station No RF with 72-110V Isolated Power Adapter	3	2	1	1 each	Yes	No
7170-0798	70-0798 Windows Docking Station 5X RF with 12-16V Auto Power Adapter		2	1	1 each	Yes	5X