



a **TEAM GJ** brand

GETAC G140 TABLET DOCKING STATION

Built for mission critical environments, the Getac G140 Tablet Docking Station delivers a secure, reliable, and rugged solution for the Getac G140 14-inch tablet across military, transport and logistics, and manufacturing operations. Designed to integrate seamlessly into demanding workflows, it maintains a clean, streamlined footprint while supporting efficient, uninterrupted use in the field. Its slim profile helps optimize in-vehicle and mobile workstation space without compromising the durability and performance required to keep operations moving.

TECHNICAL SPECIFICATIONS

WEIGHT	HEIGHT	WIDTH	DEPTH
2.5 lbs / 1.13 kg	11.7 in / 29.72 cm	12.5 in / 31.75 cm	2.5 in / 6.35 cm

ACCESSORIES

- Getac 120W Power Adapter w/ Bare Wire Lead (7300-0516)
- Getac 120W Power Adapter w/ 12V DC Socket Plug (7300-0471)
- Lind Isolated 12-32Vdc Bare Wire Power Supply (7300-0413)
- Lind Isolated 20-60Vdc Bare Wire Power Supply (7300-0412)
- Lind Isolated 72-110 Vdc Bare Wire Power Supply (7300-0416)

CERTIFICATES & TESTING

- Getac Certified
- Vibration Tested: MIL-STD 810H Operational/ Non-Operational
- Cycle Test: Latch, Lock, and Docking Connector - 30,000 Cycles
- Environmental: Thermal Shock; High/Low Temperature Operational & Storage
- FCC, RoHS Certified
- E-Mark
- SAE Standard J1455 Crash Test



FEATURES & BENEFITS

- Compatible with the Getac G140 tablet
- Getac certified electronics
- One-hand docking and release for efficient use
- Slim profile maximizes available space in tight vehicle and mobile workstation environments
- Accommodates the tablet's hard handle and high-capacity battery accessories
- Allows access to all tablet control buttons while the tablet is docked
- Downward facing rear ports with integrated cable management
- Floating docking connector ensures reliable pogo pin connection in rugged environments
- Built-in stylus holder
- Keyed lock for security
- Full and lite port replication options to align setup to peripheral and budget requirements
- Optional QUAD RF SMA pass-through
- VESA 75mm mounting pattern with 1/4 -20 1" studs
- Grade 5 1/4-20 nut and washer hardware provided, black zinc coated, recommended torque is 65 in-lbs.
- 3-Year Limited Warranty. Extended warranty options available.
- Power Input: 19V
- Operating Environment: -20°C–50°C (-4°F–122°F)
- Storage Environment: -40°C–85°C (-40°F–185°F)



GAMBERJOHNSON.COM
+1 (800) 756-9198
SALES@GAMBERJOHNSON.COM



MOUNT IT. POWER IT. CARRY IT.

GETAC G140 TABLET DOCKING STATION

PORT REPLICATION

- (1) USB-A 2.0 (front)
- (1) USB-C 2.0 (front)
- (2) USB-A 3.2
- (1) USB-C 3.2
- (1) RJ45 Ethernet
- (1) RS232 Serial (5V powered on pin 9)
- (1) HDMI
- Power Input: 19 Vdc
- QUAD SMA RF Pass-through (GPS/CELL/WIFI/ MIMO) optional



PRODUCT SELECTION

ITEM NUMBER	DESCRIPTION	USB-A 2.0	USB-C 2.0	USB-A 3.2	USB-C 3.2	ETHERNET RJ45	SERIAL RS232	HDMI	ANTENNA RF
7160-2212-00	Docking Station, Full Port, No RF	1 (Front)	1 (Front)	2	1	1	1	1	None
7160-2212-04	Docking Station, Full Port, QUAD RF	1 (Front)	1 (Front)	2	1	1	1	1	QUAD SMA
7160-2212-10	Docking Station, Lite Port, No RF	1 (Front)	1 (Front)	2	1	1	1		None
7160-2212-14	Docking Station, Lite Port, QUAD RF	1 (Front)	1 (Front)	2	1	1	1		QUAD SMA
7160-2236-00	Cradle, No RF								None
7160-2236-04	Cradle, QUAD RF								QUAD SMA
GETAC G140 KITS: INCLUDE POWER ADAPTER									
7170-1283-00	Kit: Docking Station, Full Port, No RF + 12V DC Socket Plug Power Adapter	1 (Front)	1 (Front)	2	1	1	1	1	None
7170-1283-04	Kit: Docking Station, Full Port, QUAD RF + 12V DC Socket Plug Power Adapter	1 (Front)	1 (Front)	2	1	1	1	1	QUAD SMA
7170-1283-10	Kit: Docking Station, Lite Port, No RF + 12V DC Socket Plug Power Adapter	1 (Front)	1 (Front)	2	1	1	1		None
7170-1283-14	Kit: Docking Station, Lite Port, QUAD RF + 12V DC Socket Plug Power Adapter	1 (Front)	1 (Front)	2	1	1	1		QUAD SMA
7170-1284-00	Kit: Cradle, no RF + 12V DC Socket Plug Power Adapter								
7170-1284-04	Kit: Cradle, QUAD RF + 12V DC Socket Plug Power Adapter								QUAD SMA
7170-1285-00	Kit: Docking Station, Full Port, No RF + Bare Wire Power Adapter	1 (Front)	1 (Front)	2	1	1	1	1	None
7170-1285-04	Kit: Docking Station, Full Port, QUAD RF + Bare Wire Power Adapter	1 (Front)	1 (Front)	2	1	1	1	1	QUAD SMA
7170-1285-10	Kit: Docking Station, Lite Port, No RF + Bare Wire Power Adapter	1 (Front)	1 (Front)	2	1	1	1		None
7170-1285-14	Kit: Docking Station, Lite Port, QUAD RF + Bare Wire Power Adapter	1 (Front)	1 (Front)	2	1	1	1		QUAD SMA



GAMBERJOHNSON.COM
+1 (800) 756-9198
SALES@GAMBERJOHNSON.COM



MOUNT IT. POWER IT. CARRY IT.